

LIVE TO PLAY LIVE®

cry baby
CANTRELL



JIMDUNLOP.COM

DUNLOP MANUFACTURING, INC. P.O. BOX 846 BENICIA, CA 94510 U.S.A. TEL: 1-707-745-2722 FAX: 1-707-745-2658
92503009532 REV.A

JERRY CANTRELL
JC95 SIGNATURE CRYBABY WAH OWNER'S MANUAL

JC95 SIGNATURE CRYBABY WAH

POWER

The Jerry Cantrell Signature Wah can be powered by one 9-volt battery (accessed via the bottom of the pedal), a Dunlop ECB003 AC adapter (ECB003E in Europe) or a Dunlop DCB10 DC Brick power supply.

SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the JC95's Instrument jack.
- Run another shielded instrument cable from the JC95's Amplifier jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click".
- For a brighter toe down position, rotate the Fine Tune knob clockwise to extend the high end of the sweep range. For a darker toe down position, rotate the Fine Tune knob counterclockwise.

SPECIFICATIONS

Filter Parameter

• Heel Down	320 Hz ~ 390 Hz
• Toe Down, Fine Tune Adjustable	
Fine Tune Max	1700 Hz ~ 2070 Hz
Fine Tune Min	1050 kHz ~ 1270 Hz
Input Impedance	1MEG Ω
Output Impedance	10K Ω
Bypass	Hard Wired
Maximum Input Level	-11.5dBV (@ Filter's Center Frequency)
Maximum Output	+6dBV
Maximum Gain (Toe Down)	+20dB @ 1.4 kHz ~ 1.8 kHz
Maximum Gain (Heel Down)	+18dB @ 320 Hz ~ 390 Hz
Signal to noise	Heel Down >97dBV, Toe Down >89dBV
	'A' weighted
	1mA @9V DC (9mW no load)

Power

NOTE: 0DBV REF = 1VRMS

