

# User's Manual

## Minimal Tuner with BJF Buffer

Thank you for your purchase of the Minimal Tuner with BJF Buffer by One Control.

The BJF Buffer is the perfect tool for any guitarist/bassist with a demanding Pedalboard, it ensures that your tone is carried throughout your entire setup without losing the important characteristics of your tone. Minimal Tuner combine all the features of BJF buffer and KORG Flashback Mini Tuner, it is perfect as the "start unit" of a pedalboard. Not like other buffers, the BJF buffer doesn't change the tone, just has the original tonal signal buffered then output.

### - Specifications:

Scale: 12-note equal temperament

Detection range: E0 (20.60 Hz)–C8 (4186 Hz)

Calibration range: A4 = 436–445 Hz (1 Hz steps)

Detection accuracy: +/-0.1 cent

Input impedance: 1 M-ohm (tuner on)

Output impedance: <1K-ohm (tuner off)

Power supply: CR1632 lithium battery (3V) x 2 or AC adapter (9V Negative Center)

Current consumption: maximum 40 mA

Dimensions (W x D x H): 45mm x 95 mm x 48 mm/1.77" x 3.74" x 1.89"

Weight: 137 g/4.83 oz (without battery)