

CARL MARTIN



Manual

The CARL MARTIN Rock Drive is a 9V-battery-powered pedal designed to emulate the sound of a hard driven tube amp, responsive to individual playing dynamics without altering the basic tone of the guitar.

The Attack (mid) and Edge (treble) controls give access to a variety of flavours within this type of distortion style, without compromising sonic quality.

The CARL MARTIN Rock Drive is capable of emulating tones from a smoking Twin to a beefed up JCM 800, without low-string mush or raspy highs.

The CARL MARTIN Rock Drive is true bypass and features an AC adapter jack.

Power Requirements

Battery: The Rock Drive requires a 9V battery. To replace the battery, carefully remove the back panel by loosening and removing the 4 screws, install the new battery and then re-install the back panel.

Power consumption: max. 12 mA

Power supply: 9 V DC (regulated), 50 mA minimum, 2.1 mm female plug, center negative (-)

ATTENTION: Please Use DC Power Supply Only!
Failure to do so may damage the unit and void the warranty.

Specifications

Input.....	1M Ohm
Output.....	100 Ohm
S/N Ratio.....	56dB
Gain Max.....	48db
Attack (Tmiddle).....	+20db 1Khz
Edge (treble).....	+20dB 12kHz
Dimensions	120 (W) x 95 (D) x 56 (H) mm 4.72" (W) x 3.74" (D) x 2.2" (H)
Weight.....	350g / 0,78lbs

Warranty: Carl Martin Research warrants the manufacturing, material and proper operation for a period of one year from date of purchase. Carl Martin will replace defective parts, make necessary repairs or replace the unit at the discretion of our technicians. The warranty applies only to the original purchaser of this product, and excludes any damage or faulty operation resulting from misuse, neglect or unauthorized service.

HandMade in Denmark

East Sound Research Raadmandsvej 24 8500 Grenaa Denmark Phone: +4586325100
E-Mail: info@carlmartin.com

