

THE ORIGINAL SINCE 1967



[jimdunlop.com](http://jimdunlop.com)

92503011167REVB

cry baby®

# GCRED95 ORIGINAL CRY BABY® WAH

## POWER

The Cry Baby Wah can be powered by one 9-volt battery (accessed via the bottom of the pedal), a 9-volt AC adapter such as the Dunlop ECB003/ECB003E, or the DC Brick™ and Iso-Brick™ power supplies.

## SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the GCRED95's INSTRUMENT jack.
- Run another shielded instrument cable from the GCRED95's AMPLIFIER jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click."
- Rock your foot back and forth on the pedal to instantaneously change the Cry Baby Wah's effect on your sound.

## SPECIFICATIONS

### Impedance

Input	800 k $\Omega$
Output	10 k $\Omega$

### Filter Parameter

Low Pass	350 Hz ~ 450 Hz
High Pass	1.5 kHz ~ 2.5 kHz

### Maximum Level

Input	-8.0 dBV
Output	+10 dBV

### Maximum Gain

Heel Down	+19.5 dB
Toe Down	+19 dB

### Signal to Noise Ratio\*

Heel Down	98 dBV
Toe Down	89 dBV

### Current Draw

900 $\mu$ A

\*OdBV = 1V<sub>RMS</sub>, A-weighted

